

PEN STYLE GAS LEAK DETECTOR

MR-103C

FEATURES

- Portable gas leak detector MR-103C was developed to avoid CO gas which is fatally dangerous. It is a very portable and diffusion type detector.
- It has a high quality semiconductor sensor, automatic zeroing function, visual & audible alarms and simple using switches. It is very portable & subminiature model.

SPECIFICATIONS

Detectable Gas	CO gas
Sensor type/Detection method	Semiconductor / Diffusion
Detection indication	Green(POWER), Yellow(50~300ppm), Red(300ppm~)
Alarm Type	Buzzer 80dB at 50cm
Battery	Alkaline AA 1.5V × 2EA
Power voltage	DC 3V, MAX 180mA, 1.2w
Duration of use	MAX 10 hours
Operating temp	-20°C ~ +50°C, 0% ~ 95%RH
Material/Dimension/Weight	ABS/190(L) × 33(Ø) / 100g(including batteries)
Approval	CE, FCC

